



Auto Attendant Changes

Greeting changes

Black type = instruction
Blue type = screen display

Feature 983

Log: 102 XXXX (Admin mb 102 and password) OK

Admin
MBOX AA OTHR

Press soft key under AA

Auto Atdt Admin
GRTG TABLE LINES

Press soft key under GRTG

Grtg Admin
GRTG AA

Press soft key under GRTG

Greeting:
RETRY OK

Enter the number assigned to the "Grtg" you wish to change. then OK

Greeting 1
RETRY PLAY REC

Press PLAY to listen to the greeting to ensure you are about to change the correct one, if you are NOT at the greeting you want, Press RETRY and enter the next number (2). Continue until you reach the desired greeting. Once you are at the correct greeting, press REC to record your greeting, press OK when finished

RLS when finished